

## Toroidal transformers • 56 0xx - P1S1 series

### 12V halogen lamps

Power [VA]	Part Number	Montage*	Prim. Voltage [V]	Sec. Voltage [V]	Sec. Current [A]	No Load Voltage U <sub>0</sub> [V]	Fuse (Sec.) [A]	Dimensions (p*v) / Weight [mm / kg]
15	56 021 - P1S1	S	230	11,8	1,27	13,7	1,25	62 x 32 / 0,31
30	56 022 - P1S1	S	230	11,8	2,54	13,8	2,50	74 x 34 / 0,44
50	56 001 - P1S1	S	230	11,8	4,24	13,5	5,00	84 x 34 / 0,63
80	56 002 - P1S1	S	230	11,8	6,78	13,5	8,00	95 x 36 / 0,87
120	56 003 - P1S1	S	230	11,8	10,17	13,1	12,50	96 x 47 / 1,20
160	56 004 - P1S1	S	230	11,8	13,56	12,9	16,00	110 x 46 / 1,50
200	56 005 - P1S1	S	230	11,8	16,95	12,7	20,00	116 x 48 / 1,90
250	56 006 - P1S1	S	230	11,8	21,19	12,8	25,00	118 x 55 / 2,20
300	56 007 - P1S1	S	230	11,8	25,42	12,6	25,00	118 x 60 / 2,40
400	56 008 - P1S1	S	230	11,8	33,90	12,6	35,0	140 x 55 / 3,10
500	56 009 - P1S1	S	230	11,8	42,37	12,6	50,0	140 x 62 / 3,50

### 12V halogen lamps with auto-reset thermal switch

Power [VA]	Part Number	Montage*	Prim. Voltage [V]	Sec. Voltage [V]	Sec. Current [A]	No Load Voltage U <sub>0</sub> [V]	Fuse (Sec.) [°C]	Dimensions (p*v) / Weight [mm / kg]
15	56 031 - P1S1	S	230	11,8	1,27	13,7	110	62 x 32 / 0,31
30	56 032 - P1S1	S	230	11,8	2,54	13,8	110	74 x 34 / 0,44
50	56 011 - P1S1	S	230	11,8	4,24	13,5	110	84 x 34 / 0,63
80	56 012 - P1S1	S	230	11,8	6,78	13,5	110	95 x 36 / 0,87
120	56 013 - P1S1	S	230	11,8	10,17	13,1	110	96 x 47 / 1,20
160	56 014 - P1S1	S	230	11,8	13,56	12,9	110	110 x 46 / 1,50
200	56 015 - P1S1	S	230	11,8	16,95	12,7	110	116 x 48 / 1,90
250	56 016 - P1S1	S	230	11,8	21,19	12,8	110	118 x 55 / 2,20
300	56 017 - P1S1	S	230	11,8	25,42	12,6	110	118 x 60 / 2,40

\*) Mounting:

- S - standard mounting kit
- B - center potted with threaded brass insert
- H - center potted with through hole
- D - to DIN 35